




NUMBER TWO 1979

### Computers are NIT-PICKERS:

While "the book" may state that spacing in BASIC programs is "optional", there's always the exception that proves the rule... If there are spaces between the name of an array or matrix and the parentheses that encloses the array row/column variable(s) or numbers, Computer may drop the leading parentheses and come up with an error message. Therefore:

Array references should look like this:

<b>TYPE</b>	<b>DO NOT TYPE</b>
A(30)	A (30)
	 (space)

Remember that NO SPACES SHOULD BE USED IN ARRAY VARIABLES. Pretty soon this will become habit, and Computer will, in turn, break its own bad habit of spraying you with "couthless" ERROR messages!

### You Can't Go Wrong Using English Spacing In BASIC

Related to the "nit-picking" problem above, beginning programmers should develop the habit of using spaces between words, symbols, etc. (just as a High School English teacher would like!) Doing this doesn't cost a single byte of RAM: Since each statement is checked and tokenized as it enters the computer, the spaces aren't stored anyhow...they are used only in the interpretation portion of input processing. Remembering this can make your programs more "human" and easier to RUN and read, and can avoid all kinds of potential confusion on the part of your computer!

### Don't Use "Reserved" BASIC WORDS As Variables!

If you use a BASIC keyword or other "reserved" word that your computer may interpret as a function or statement rather than a variable, sooner or later it WILL so interpret! Learn to avoid such problems as use of the variable name LETTER (includes the word LET), FORTY (the computer may see this as if it were FOR TY), NEXT (used as a variable name), and the like. You get the idea!

### A Somewhat "NOTTY" Problem

The BASIC interpreter has difficulties when you combine logical operators (NOT, =, <, >, <=, >= and <>) with the operator NOT. In fact in some cases it just plain stops! When this happens, all contact between the keyboard and the Computer itself is lost, and even pressing SYSTEM RESET doesn't help. The only recourse at this point is to turn the system OFF and then ON again. This licks the problem with NOT, but simultaneously causes everything in RAM to be lost.


The best solution, as usual, is an ounce of prevention: ALWAYS ENCLOSE THE NOT AND ITS ASSOCIATED VARIABLE IN PARENTHESES, like these examples:

```
100 PRINT A = (NOT B)
```

```
100 PRINT A < (NOT B)
```

and so forth...

## DISC RECORDER 810™



Once in a while your disc may refuse to talk to your computer. The computer will inform you of this problem by typing "ERROR-138". If this should occur, use the following procedure:

1. Remove the diskette.
2. Turn the Disk Drive OFF, then ON.
3. Replace the diskette and try the disk operation again.

## CASSETTE

Your computer sometimes gets confused after you hit **SYSTEM RESET** and refuses to write to the cassette. To insure that your BASIC programs are properly written to the cassette, you should always enter them by typing LPRINT **RETURN** before typing CSAVE. If you don't have a printer, the system will print out "ERROR-138" which you should ignore.





## Chapter Reference Tabs

The material printed on this page is for your convenience in organizing your **Basic Reference Manual**. Simply cut out the tabs on the lines with a pair of scissors and insert them in clear plastic tab holders (available at any stationery store). Fasten the tabs to each chapter title page or appendix cover page and you are in business!

INTRODUCTION TERMS  
and CONVENTIONS

PROGRAMS and  
PROGRAM CONTROLS

BRANCHING  
and LOOPING

VARIABLES, OPERATORS,  
and PRECEDENCE

INPUT / OUTPUT  
OPERATIONS

ARITHMETIC  
FUNCTIONS

STRINGS and  
STRING FUNCTIONS

ARRAYS  
and MATRICES

ATARI GRAPHICS

SOUND and GAMES:  
SPECIAL FEATURES

ADVANCED PROGRAMM-  
ING HINTS & TIPS

GLOSSARY / INDEX

ERROR MESSAGES

BASIC KEYWORDS

USER PROGRAMS  
& SAMPLE ROUTINES

CONVERSION TABLES

ATASCII  
CHARACTER SET

KEYBOARD OPERATIONS  
and EDITING